



**Standards:**

- BS 5266 Part 1:2005,
- BS EN 60598-2-22:2002,
- BS5499-3:2002,
- FSD PPA 104(A) 4<sup>th</sup> Revision,
- FSD COP Clause 5.10 EXIT Sign.

**Features:**

- Wall-mount.
- More reliable for using Ni-Cad / Ni-Mh battery.
- AC and DC mode are in same lumen output.
- High efficiency super flux LED lamps with high performance.

**Specification:**

- Self-contained, maintained type, automatic changeover device for minimum 2 or 3 hours battery back up.

<b>Model</b>	<b>ALS-2C-LR295</b>
<b>Battery Type</b>	Sealed Ni-Cad <small>***Sealed Ni-Mh are available</small>
<b>Mode of Operation</b>	Maintained Type <small>***Flash upon fire singal are available</small>
<b>Power Consumption</b>	~3 W <small>***Adjustable</small>
<b>Emergency Duration</b>	2 Hours <small>***3 Hours are available</small>
<b>Emergency Luminance</b>	Average 100cd/m <sup>2</sup> <small>***Adjustable</small>
<b>Battery</b>	4.8V 800 mAh
<b>Line Voltage</b>	A/C 220V 50Hz +/-10%
<b>Recharge Period</b>	12 Hours for 2 Hours Discharge
<b>Metal Box Size</b>	260L x 100H x 50D
<b>Plate Size</b>	160L x 160H x 8D

**\*\*\*Options will be available upon request**