



Specification:

- Self-contained, maintained type, automatic changeover device for minimum 2 or 3 hours battery back up.

Standards:

- BS 5266 Part 1:2005,
- BS EN 60598-2-22:2002,
- BS5499-3:2002,
- FSD PPA 104(A) 4th Revision,
- FSD COP Clause 5.10 EXIT Sign.

Features:

- Lamp Source: T8 fluorescent.
- Red LED to indicate mains supply and healthy charging status.
- Test Button to allow easy checking of luminaries operation.
- Optional Metal housing constructed of galvanized steel with EPOXY powder coating.

Model	ALS-2C-120W + FB120 / 220	ALS-2C-130W + FB130 / 230	ALS-2C-140W + FB140 / 240	ALS-2C-165W + FB165 / 265
Suitable to	T8: 18/20W	T8: 30W	T8: 36/40W	T8: 58/65W
Battery Type	Sealed Ni-Cad <small>***Sealed Ni-Mh are available</small>			
Mode of Operation	Maintained Type <small>***Non-maintained type are available</small>			
Emergency Output	0.25 BLF <small>***Adjustable</small>			
Emergency Duration	2 Hours <small>***3 Hours are available</small>			
Battery	6V 2.0Ah	8.4V 2.0Ah	8.4V 2.0Ah	9.6V 2.0Ah
Line Voltage	A/C 220V 50Hz +/-10%			
Operation Temperature	0 - 50°C			
Recharge Period	12 Hours for 2 Hours Discharge <small>***Options will be available upon request *Metal housing are available</small>			